

E1445A Arbitrary Function Generator Component Level Information

Information in this packet applies to the following assemblies:


- 1. E1445-66502 PC Assembly
- 2. E1445-66503 PC Assembly
- 3. E1445-66511 PC Assembly

This packet includes:

- 1. Component locators
- 2. Schematics
- 3. Parts lists with Agilent and manufacturer's part numbers




E1445-66502 Component Locator




Agilent E1445A Arbitrary Waveform Generator


E1445-66502 Component Locator


	01 2 4 20 174	J102	_ 2 .
AGND1 3	2 4 AGNU1	G115 1 '	2 GND
AGND1 5	6 AGND1	GND 5	GND GND
-24VA - 2	-24VA	nc 🗘	R♥ nc
+24VA	+24VA	nc 😽	B nc
-5.2V3 11	-5.2V3	GND 11	I2 GNU
+5V3	+5V3	VCC 11	VCC
-12V3 15	-12V3	GND 15	IE GND
+12V3 13	18 +12V3	VEE 13	18 VEE
nc 🙀	20 nc	GND 17	GNU
nc 🔾	22 nc	VTT	SS ALL
GND 21	GND	GND 21	
GND 23		nc 🔀	24 IND
-24V 25	26 -24V	CND L25	
+247	28 +24V	VCC 27	ZB VCC
GND 29	30 GND	GND 29	30 GND
-12V 31	32 -12V	VEF 31	32 VEE
+12V 33	34 +137	CND 33	34 CND
CND 35	36 CND	VTT 35	36 VTT
+5V2 37	38 1573	CND 37	38 CND
CND 39	40 CND	CND 39	40 CND
GND 41	42 CND	CND 41	42 CND
GND 43	44 GND	HSD(15) O Pg 2 43	44 GNDHSD(14)R
' 95	46,	HSD(15)R GND 45	46 GND
nc \$7	48 nc	HSD(13) O Pg 2 47	CND HEDGESON
nc 19	nc 50 GND	HSD(13) CAID L 49	50 GNUHSD(12)R Pg 2 O HSD(12)
GND 51		HSD(13)R GND 51 HSD(11) O 51	CND HODGEN
GND 51	54 GND Pg 2 RSTB*	HSU(11) O 3 1 53	54 GNDHSD(10)R
DSTB* OPg 2 nc \$5	56 Pg 2	HSD(11)R GND 55	54 Pg 2 O HSD(10)
DS1B* O 3 57	56 Pg 2 O ASTB*	HSD(9) O Pg 2 55	58 GNDHSD(8)R
GND 57 AD(0) Pg 2-4,8,11 61	60 Pg 2-4,8,11 C AP(1)	HSD(9)R GND 59	58 GAB Pg 2 O HSD(8)
AD(2) O Pg 2-4,8,11 61	62 Pg 2-4,8,11 O AD(1)	HSD(7) O Pg 2 59	(;NI)HSD(6)R
AD(2) O-3 - 1,010	64 O AD(3)	HSD(7)R GND 63	62 Pg 2 O HSD(6)
GND 63 65		HSD(5) O	(;NI)HSD(4)R
AD(4) OPg 2-4,8,11 67	66 GNU Pg 2-4,8,11 AD(5)	HSD(5)R GND	= O HSD(4)
AD(6) O Pg 2-4,8,11 67		HSD(3) O	
GND 71	72 GND	HSD(3)R GNU 71	70 nc 72 nc
ac ()	nc nc	GND 73	Z4 GNU
DACEN O	76 nc	GND 75	GND GND
+5V1 73	78 +5V1	DACCLK O	ZR GND
GND 70	80 GND	DACCLKR GNU 70	BO GND
GND 79 79			VEE
`\$¹_нн_	80 BZ GNU	VEE HHI H	θ2 B2 VEE



NOTE:
ALL TESTPOINTS ARE CIRCUIT SIDE TESTPOINTS ONLY>










Agilent E1445A Arbitrary Waveform Generator


Input Connectors and Power Supplies


E1445-66502 page 1 of 15


















Offset Current Section


E1445-66502 page 4 of 15




















Attenuator

E1445-66502 page 8 of 15





E1445-66502 page 10 of 15



THESE TWO SYMBOLS ARE
THE SAME NET NAMES


GND

GND

Agilent E1445A Arbitrary Waveform Generator


Analog Test

E1445-66502 page 11 of 15



Analog Block

E1445-66502 page 12 of 15



Major Signal Flowchart

E1445-66502 page 13 of 15

C619 1	C615 1 C616 1 C617 1 C618 1	C609 1 C610 1 C611 1 C612 1 C613 1 C614 1	E501 E502 E502 E502 E502 E501 F1/701 J102 J102 J102 J100 G103 J100 G101 J100 G102 G203 G204 G205 G206 G206 G207 G208 G207 G208 G207 G208 G208 G208 G208 G208 G208 G208 G208	
550 -6650 250 -5200	900 -7250 1450 -5650 1450 -5750 1400 -6650 550 -6650	1175 -5650 350 -6100 350 -6000 1300 -7450	2550	
CR1015 1	CR1011 I CR1012 I CR1013 I CR1014 I	CR1005 I CR1006 I CR1007 I CR1008 I CR1009 I	C620 1 C621 1 C622 1 C622 1 C622 1 C701 1 C702 1 C703 1 C704 1 C705 1 C706 1 C707 1 C708 1 C708 1 C710 1 C711 1 C712 1 C713 1 C714 1 C715 1 C716 1 C718 1 C718 1 C718 1 C718 1 C718 1 C718 1 C719 1 C710 1 C720 1 C7	
3575 -600 l	2925 75 2575 75 3275 75 3725 -1000 3700 -775 3575 -600	3575 -250 4400 -250 2225 75	600 -5500 625 -4825 2325 -4825 1850 -3150 1850 -3275 1850 -3275 1850 -3275 1850 -3275 1850 -3275 1850 -3275 1850 -3275 1850 -3275 1850 -3275 1850 -3275 1850 -3250 1850 -3550 1850 -3550 1850 -4825 1850 -3000 1850 -4800 1850 -4800 1850 -4800 1850 -1500 1850 -68500 1850 -	
R327 1	R320 1 R321 1 R322 1 R326 1	R314 1 R315 1 R316 1 R317 1 R318 1 R319 1	1701 1 1702 1 1703 1 1704 1 1705 1 1 1 1 1 1 1 1 1	
4100 -4350	3400 -4250 3400 -4150 2775 -4750 4100 -4250	3100 -5250 3800 -4850 5775 -6175 5775 -6275 3750 -3950 3750 -4250 3400 -4050 3400 -3950	900 -3500 2750 -2850 550 -3500 2750 -2850 550 -3500 2750 -2500 2750 -2500 2750 -2500 2750 -2500 2750 -2500 2750 -2200 5700 -2200 5700 -2200 5700 -2200 5700 -2200 5700 -2200 5700 -2200 5700 -2500 1900 -1500 1900 -1500 1900 -1500 1 6800 -1500 1 6700 -4450 1 5025 -8175 1 4750 -8175 1 1200 -4975 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7750 1 1200 -7755 1 1200 -7755 1 1200 -7755 1 1200 -7950 1 1200 -7950 1 1200 -7950 1 1200 -7950 1 1200 -7950 1 1200 -7950 1 1200 -7950 1 1200 -975	
R909 1	R904 1 R906 1 R907 1 R908 1	R822 1 R823 1 R824 1 R901 1 R902 1 R903 1	R401	
1500 -1350	5330 -1200 5125 -1500 2400 -1950 2400 -1750 1500 -1550	6450 -2600 6350 -1775 5975 -800 5975 -700 5750 -1775 5350 -1300 5350 -1200 5125 -1500 2400 -1950	5550 -6500 4150 -6300 4150 -6300 4150 -6300 4150 -5300 4150 -5300 4400 -5225 5775 -5575 5875 -5550 2600 -5500 2600 -5550 2800 -5550 2800 -5550 2800 -5550 3400 -5550 2300 -5875 3700 -5875 3400 -5875 3400 -5875 3400 -5875 3400 -5875 3400 -5875 3400 -5875 3400 -5825 2350 -5825 2350 -5825 2350 -5825 2350 -5825 2350 -5820 350 -5850 350 -5850 350 -5850	
1			R910 R911 R911 R9113 R9113 R9113 R9113 R9113 R9115 R	
			1950 1950 1950 1950 1950 1950 1950 1950	
			-100 -100 -100 -100 -4150 -4250 -4250 -4250 -4250 -4250 -700 -7000	
	X-Y Co	Agilent Arbitra	T101	
	mpone		6375 6375 5025 5025 5025 5025 5025 5025 5025 50	
	ent Lo		-975 -5050 -4250 -6255 -6255 -5725 -5725 -48725 -68	
	cator	n Generator	Locations of Ref. Des. Layer	
			2350	

E1445-66502 page 14 of 15

1702	U701 Pg07 U606 B Pg06
TP803	TP802 Pg08 TP801 Pg08
TP304	TP303 Pg03 TP302 Pg03
R1028 Pg10 R1027 Pg10 R1026 Pg10 R1025 Pg10 R1024 Pg10 R1023 Pg10 R1022 Pg10 R1022 Pg10 R1022 Pg10 R1021 Pg10 R1021 Pg10 R1019 Pg10 R1019 Pg10 R1019 Pg10 R1011 Pg10 R1011 Pg10 R1010 Pg10 R1010 Pg10 R1011 Pg10 R1010 Pg10 R1011 Pg10 R1010 Pg10 R1010 Pg10 R1010 Pg10 R1010 Pg10 R1010 Pg10 R1010 Pg10 R1008 Pg10 R1001 Pg10 R1008 Pg10 R1009 Pg10 R1001 Pg10 R1008 Pg10 R1008 Pg10 R1008 Pg10 R1009 Pg10 R1009 Pg10 R1009 Pg10 R1009 Pg10 R1001 Pg10 R1001 Pg10 R1005 Pg10 R1001 Pg10 R1005 Pg10 R1004 Pg10 R1005 Pg10 R1005 Pg10 R1005 Pg10 R1006 Pg10 R1007 Pg10 R1008 Pg10 R1009 Pg10 R1001 Pg10	R1027 Pg10 R1026 Pg10
R807 Pg 08 R806 Pg 08 R807 Pg 07 R731 Pg 07 R738 Pg 07 R728 Pg 07 R729 Pg 07 R721 Pg 07 R722 Pg 07 R729 Pg 07 R731 Pg 07 R731 Pg 07 R749 Pg 07 R755 Pg 07 R708 Pg 07 R708 Pg 07 R709 Pg 06 R601 Pg 06	R8 06 Pg 08 R8 05 Pg 08
R405 Pg 04 R404 Pg 04 R403 Pg 04 R402 Pg 04 R402 Pg 04 R402 Pg 04 R402 Pg 04 R401 Pg 05 R322 Pg 03 R326 Pg 03 R322 Pg 03 R321 Pg 03 R319 Pg 03 R319 Pg 03 R319 Pg 03 R3117 Pg 03 R3116 Pg 03 R3117 Pg 03 R3116 Pg 03 R3117 Pg 03 R311 Pg 03 R300 Pg 03 R301 Pg 03 R301 Pg 03 R305 Pg 03 R306 Pg 03 R306 Pg 03 R307 Pg 03 R307 Pg 03 R308 Pg 03 R309 Pg 03 R301 Pg 03 R301 Pg 03 R301 Pg 03 R302 Pg 03 R301 Pg 03 R302 Pg 03 R301 Pg 03 R301 Pg 03 R302 Pg 03 R301 Pg 03 R	R404 Pg04 R403 Pg04
L1002 Pg10 L1001 Pg10 L1001 Pg10 L704 Pg07 L703 Pg07 L702 Pg07 L701 Pg07 L502 Pg08 L501 Pg08 L501 Pg08 L206 Pg08 L206 Pg08 L206 Pg02 L206 Pg02 L207 Pg07 L208 Pg02 L208 Pg02 L209 Pg08 L201 Pg08 L201 Pg08 L101 Pg09 L102 Pg01 L103 Pg01 L102 Pg01 L103 Pg01 L104 Pg09 K904 Pg09 K906 Pg09 K907 Pg09 K907 Pg09 K908 Pg09 K908 Pg09 K908 Pg09 K909 Pg09 K909 Pg09 K901 Pg09	L1001 Pg10 L704 Pg07
CRE 03	CR6 02 Pg 06 CR6 01 Pg 06
C703 Pg07 C702 Pg07 C702 Pg07 C702 Pg07 C701 Pg07 C702 Pg06 C821 Pg06 C821 Pg06 C818 Pg06 C818 Pg06 C816 Pg06 C816 Pg06 C817 Pg06 C817 Pg06 C818 Pg06 C818 Pg06 C819 Pg06 C819 Pg06 C819 Pg06 C819 Pg06 C819 Pg06 C810 Pg06 C810 Pg06 C810 Pg06 C810 Pg06 C811 Pg06 C810 Pg06 C811 Pg06 C809 Pg06 C809 Pg06 C809 Pg06 C809 Pg06 C805 Pg06 C806 Pg06 C807 Pg06 C808 Pg06 C808 Pg06 C809 Pg06 C809 Pg06 C801 Pg06 C801 Pg06 C801 Pg06 C801 Pg07 C811 P	C702 Pg07 C701 Pg07
C219 Pg02 C218 Pg02 C217 Pg02 C216 Pg02 C215 Pg02 C215 Pg02 C214 Pg02 C211 Pg02 C211 Pg02 C211 Pg02 C211 Pg02 C211 Pg02 C211 Pg02 C210 Pg02 C200 Pg02 C200 Pg02 C200 Pg02 C200 Pg02 C201 Pg02 C205 Pg02 C204 Pg02 C204 Pg02 C204 Pg02 C204 Pg02 C201 Pg01 C102 Pg10 C102 Pg10 C101 Pg10 C102 Pg10 C1021 Pg10 C1022 Pg10 C1021 Pg10 C1021 Pg10 C1021 Pg10 C1021 Pg10 C1021 Pg10 C1022 Pg10 C1021 Pg10 C1021 Pg10 C1021 Pg10 C1022 Pg10 C1021 Pg10 C1021 Pg10 C1021 Pg10 C1021 Pg10 C1021 Pg10 C1021 Pg10 C1022 Pg01 C1022	C218 Pg 02 C217 Pg 02

Schematic Reference Page

E1445-66502 page 15 of 15

Reference		Agilent			
Designator	Qty	Part Number	Description	MPN	Manufacturer
BAG1	1	9222-1440	POUCH-STAT-DISS-CNDCT PE	9222-1440 PACK 66	MAINE POLY SPECIALTY ENTERPRISES
C1001, C1024, C401, C708	4	0160-6096	CAP-FXD 470pF +-5pct 50 V CER C0G	12065A471JAT A C1206C471J5GAC C3216COG1H471J GRM3165C1H471JD01D	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING
C1002, C1003, C704, C705	4	0160-6100	CAP-FXD 1000pF +-5pct 50 V CER C0G	12065A102JAT A C1206C102J5GAC C3216CH1H102J GRM3195C1H102JD01D	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING
C1004, C1005, C1014, C1017, C724, C726	6	0180-3744	CAP-FXD 4.7uF +-20PCT 10V TA	TAJB475M010 293D475X0010B2E3 ESVB21A475M SK-1A475M-RB T491B475M010AS	AVX VISHAY NEC ELECTRONICS ELNA KEMET ELECTRONICS
C1006, C1007, C101, C1010-C1013, C102, C103, C720, C722, C805, C806	13	0180-4287	CAP-FXD 10uF +-20PCT 35V TA	TAJD106M035 293D106X0035D2WE3 ESVD1V106M	AVX VISHAY NEC ELECTRONICS
C1008, C1009, C1022, C1023, C201, C203, C215, C301, C303-C314, C402- C406, C501-C504, C506, C508, C510, C512, C513, C515, C521, C522, C601- C604, C606, C608, C610, C612, C613, C615, C617, C619, C620, C728, C729, C801, C804, C901-C903, C905-C907	60	0160-6497	CAP-FXD 0.1uF +-10pct 50 V CER X7R	12065C104KAT A 2238 581 15649 C1206C104K5RAC C3216X7R1H104KT GRM319R71H104KA01D VJ1206Y104KXAMT	AVX YAGEO KEMET ELECTRONICS TDK MURATA MANUFACTURING VISHAY
C1015, C1016, C1018- C1021, C202, C204-C210, C216, C217, C222, C223, C505, C507, C509, C511, C514, C516-C520, C605, C607, C609, C611, C614, C616, C618, C711-C719, C721, C723, C725, C727, C904	49	0160-6736	CAP-FXD 0.01uF +-10pct 50 V CER X7R	12065C103KAT A C1206C103K5RAC C3216X7R1H103K GRM316R71H103KD01D VJ1206Y103KXAMT	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING VISHAY

Reference Designator	Qty	Agilent Part Number	Description	MPN	Manufacturer
C1025, C214, C221, C709	4	0160-5961	CAP-FXD 22pF +-5pct 50 V CER C0G	08055A220JAT A C0805C220J5GAC C2012COG1H220J GRM2165C1H220JD01D VJ0805A220JXAMT	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING VISHAY
C1026, C212, C213, C219, C220, C523, C524, C621, C622	9	0160-5962	CAP-FXD 15pF +-5pct 50 V CER C0G	08055A150JAT A C0805C150J5GAC C2012COG1H150J GRM2165C1H150JD01D	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING
C211, C218, C730, C731, C908	5	0160-5942	CAP-FXD 1pF +-0.25pF 50 V CER C0G 2012	08051A1R0CAT A C0805C109C5GAC C2012C0G1H010C GRM2165C1H1R0CD01D	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING
C302, C707	2	0160-5968	CAP-FXD 82pF +-5pct 50 V CER C0G	08051A820JAT A C0805C820J5GAC C2012COG1H820J GRM2165C1H820JD01D	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING
C701, C710	2	0160-5979	CAP-FXD 1.5pF +-16.67pct 50 V CER C0G	08055A1R5CAT A C0805C159C5GAC C2012COG1H1R5C GRM2165C1H1R5CD01D GRM40-001COG1R5C050	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING N TOOL AND DIE
C702, C703, C706	3	0160-6104	CAP-FXD 2200pF +-5pct 50 V CER C0G	12065A222JATRA C1206C222J5GAC C3216C0G1H222J GRM3195C1H222JD01D	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING
CR1001-CR1004	4	1902-1565	DIODE-ZNR 4.7V 5pct TO-236 (SOT-23)	BZX84-C4V7 BZX84C4V7LT1G BZX84-C4V7	PHILIPS ON SEMICONDUCTOR NXP
CR1005, CR1006, CR1013-CR1015, CR501- CR505, CR601-CR605	15	1906-0291	DIODE-DUAL 70V 100MA T0-236AA	BAV99 BAV99 BAV99LT1G BAV99X_ BAV99	PHILIPS FAIRCHILD SEMICONDUCTOR ON SEMICONDUCTOR INFINEON TECHNOLOGIES NXP

Reference		Agilent			
Designator	Qty	Part Number	Description	MPN	Manufacturer
CR1007, CR1008	2	1902-1512	DIODE-ZNR 7.5V 5pct TO-236 (SOT-23)	BZX84C7V5LT1G BZX84C7V5	ON SEMICONDUCTOR PHILIPS
				BZX84C7V5	NXP
				DZX04C7V5	NAP
CR1009, CR1010,	4	1902-1603	DIODE-ZNR 3.9V 5pct PD=1.5W IR=25UA	1SMB5915BG	ON SEMICONDUCTOR
CR1011, CR1012					
CR201, CR202	2	0122-0172	DIODE-VVC 29PF 10pct C 3/C25-MIN=5	BBY40	PHILIPS
				MMBV109LT1G	ON SEMICONDUCTOR
				BBY40	NXP
CR301, CR401	2	1902-1544	DIODE-ZNR 10V 5PCT TO-236(SOT-23) PD35	B7X84C10	PHILIPS
JINOUI, UNTUI	_	1302-1344		BZX84C10LT1G	ON SEMICONDUCTOR
				BZX84C10	NXP
				D270-1010	1374
CR901, CR903	_	1901-1339	DIODE-V-SUPPR DO-214AB	SMCJ12-E3/57T	VISHAY
CR902, CR904	_	5185-8472	Lifetime buy for 1901-1386		
CR902, CR904a	_	1901-1386	DIODE-SWITCHING 100V 1A	BAS78B	OSRAM
E501, E502, E601, E602,	7	9170-1421	CORE-SHIELDING BEAD IMAX 1500MA	MI1210K600R-10	STEWARD
E901, L1003, L1004					
FL701	_	9135-0455	FILTER-LOW PASS PC PIN-TERMS	2045	KR ELECTRONICS
HSQ1005, HSQ1006	2	1205-1295	HEAT SINK TO-5/TO-39-CS ; HEAT SINK ; FOR		INTL ELECTRONIC RESEARCH
				TXBF-032-025B	CTS
J101, J102	2	1252-4572	CONN-POST TYPE .050-PIN-SPCG-MTG-END	5-104550-8	TYCO ELECTRONICS AMP
J901	1	1250-2012	CONNECTOR-RF BNC FEMALE PC-W-STDFS	5227676-1	TYCO ELECTRONICS AMP
K701-K706, K901-K904		0490-1775	RELAY-REED 1A 1A 200VDC 5VDC-COIL	9200-0055	COTO WABASH
K801, K802, K803, K804		0490-2317	RELAY 2C 5VDC-COIL 1A 110VDC	TQ2SA-L2-5V	MATSUSHITA
L1001, L1002, L102,	5	9170-1431	CORE-SHIELDING BEAD	HF50ACB-453215	TDK
L103, L105					
L101		9140-1113	INDUCTOR 10uH +-5pct 3.4W-mmX4.8LG-mm (GOWANDA ELECTRONICS
L201, L205	2	9140-1098	INDUCTOR 150nH +-5pct 2.8W-mmX3.4LG-mm		TDK
				KL32TR15J	KOA
_202, L206	2	9140-1100	INDUCTOR 330nH +-5pct 2.8W-mmX3.4LG-mm	NI V32T-R33.I-PF	TDK
2202, 2200	-	0140 1100	in booter deciment oper 2.000 minixo.420 mini	KL32TR33J	KOA
				11000	NO/Y
L203, R206, R817	3	0699-1360	RESISTOR 46.4 +-1pct .125W TKF TC=0+-100	CRCW120646R4FKE_	VISHAY
				RK73H2BT_46R4F	KOA
				MCR18F46R4	ROHM
				232272464649	YAGEO
204 504 502	5	9140-1206	INDUCTOR 100nH +-5pct 2.8W-mmX3.4LG-mm	NLV22T D40 LDE	TDK
L204, L501, L502, L601, L602	5	9140-1200	TOCTOR TOUTIN +-SPCL 2.899-MIMAS.4LG-MM	KL32TR10J	KOA
LOU1, LOU2				KL321K10J	NOA

Reference		Agilent			
Designator	Qty	Part Number	Description	MPN	Manufacturer
L701	1	9100-1639	INDUCTOR RF-CH-MLD 150uH +-5pct	1537-84 15M153J IM-4 150UH 5%	AMERICAN PRECISION INDUSTRIES GOWANDA ELECTRONICS VISHAY
L702	1	9100-1633	INDUCTOR RF-CH-MLD 68uH +-5pct	1537-68 15M682J IM-4 68UH 5%	AMERICAN PRECISION INDUSTRIES GOWANDA ELECTRONICS VISHAY
LBL1	1	9320-6241	LBL-PG-PTR; .625-IN-WD X .25-IN-LG	9320-6241	BRADY
LBL2		7121-0850	LABEL-ANTISTATIC 1.81-IN-WD 2.5-IN-LG	7101 7101 7121-0850	R S HUGHES 3M GM NAMEPLATE
LBL3	1	7121-5729	LBL-LNE-PTR; 1.5-IN-WD X .25-IN-LG	THT-45-457-10	BRADY
MP1		0380-1958		BR5172-06-35	LYN-TRON
MP2		0590-1445	THREADED INSERT-NUT M3 X 0.5 1.5-MM-LG		CAPTIVE FASTENER PENN ENGINEERING & MFG
PCB1	1	E1445-26502	PC BLNK SMT	E1445-26502	SANMINA-SCI
Q1001, Q1006	2	5961-3088	LTB OF 1854-1114		
Q1001, Q1006a	1	1854-1114	TRANSISTOR NPN SI TO-39 PD 3.5W FT 1GHZ		
Q1002, Q1005	2	5065-6691	LTB FOR E1445-66502		
Q1002, Q1005a	1	1853-0625	TRANSISTOR PNP SI TO-39 PD=3.5W FT=1GH	MRF545	MICROSEMI
Q1003, Q1004, Q302	3	1854-1037	TRANSISTOR NPN SI TO-236AA PD=350MW	MMBT3904 SST3904T116 MMBT3904LT1G	FAIRCHILD SEMICONDUCTOR ROHM ON SEMICONDUCTOR
Q201, Q202	2	1854-1148	TRANSISTOR NPN SI SOT-23 (TO-236AB)	MMBTH10 MMBTH10LT1G	FAIRCHILD SEMICONDUCTOR ON SEMICONDUCTOR
Q203	1	1855-0734		2N7002-T1-E3 2N7002 2N7002 SN7002NX_ 2N7002	VISHAY FAIRCHILD SEMICONDUCTOR PHILIPS INFINEON TECHNOLOGIES NXP
Q301	1	1853-0567	,	MMBT3906 SST3906T116 MMBT3906LT1G	FAIRCHILD SEMICONDUCTOR ROHM ON SEMICONDUCTOR

E1445-66502 Parts List

Reference		Agilent	ı	I	
Designator	Qty	Part Number	Description	MPN	Manufacturer
R1001	1	0699-1422	RESISTOR 196 +-1pct .125W TKF TC=0+-100	CRCW1206196RFKE_ RK73H2BT_1960F MCR18F1960 232272461961L	VISHAY KOA ROHM YAGEO
R1002, R217, R228, R229, R230, R231, R408, R502, R505, R602, R607	11	0699-1344	RESISTOR 10 +-1pct .125W TKF TC=0+-100	CRCW120610R0FKE_ RK73H2BT_10R0F MCR18F10R0 232272461009L	VISHAY KOA ROHM YAGEO
R1003	1	0699-1426	RESISTOR 287 +-1pct .125W TKF TC=0+-100	CRCW1206287RFKE_ RK73H2BT_2870F MCR18F2870 232272462871	VISHAY KOA ROHM YAGEO
R1004, R1007, R104, R211, R214	5	0699-1358	RESISTOR 38.3 +-1pct .125W TKF TC=0+-100	CRCW120638R3FKE_ RK73H2BT_38R3F MCR18F38R3 232272463839	VISHAY KOA ROHM YAGEO
R1005, R1008, R712, R715	4	0699-1425	RESISTOR 261 +-1pct .125W TKF TC=0+-100	CRCW1206261RFKE_ RK73H2BT_2610F MCR18F2610 232272462611L	VISHAY KOA ROHM YAGEO
R1006	1	0699-1427	RESISTOR 316 +-1pct .125W TKF TC=0+-100	CRCW1206316RFKE_ RK73H2BT_3160F MCR18F3160 232272463161	VISHAY KOA ROHM YAGEO
R1009, R1010, R1023, R1024, R203, R221	6	0699-1415	RESISTOR 100 +-1pct .125W TKF TC=0+-100	CRCW1206100RFKE_ RK73H2BT_1000F MCR18F1000 232272461001L	VISHAY KOA ROHM YAGEO
R101, R1011, R1012, R102, R212, R213, R301, R322, R717, R719, R810	11	0699-1423	RESISTOR 215 +-1pct .125W TKF TC=0+-100	CRCW1206215RFKE_ RK73H2BT_2150F MCR18F2150 232272462151L	VISHAY KOA ROHM YAGEO

Reference		Agilent			
Designator	Qty	Part Number	Description	MPN	Manufacturer
R1013, R1014, R1015, R1016, R1017, R1018, R1019, R1020	8	0699-1418	'	CRCW1206133RFKE_ RK73H2BT_1330F MCR18F1330 232272461331	VISHAY KOA ROHM YAGEO
R1021, R1022, R1027, R1030	4	0699-2859	RES-FXD 51 OHM +-5PCT 1W TC 0+-200	CRCW251251R0JNE_ RK73B3AT510J MCR100J510	VISHAY KOA ROHM
R1025, R1026, R816, R818	4	0699-1374	RESISTOR 1.78K +-1pct .125W TKF TC=0+-100	CRCW12061K78FKE_ RK73H2BT_1781F MCR18F1781 232272461782L	VISHAY KOA ROHM YAGEO
R1028, R720	2	0699-1351	·	CRCW120619R6FKE_ RK73H2BT_19R6F MCR18F19R6	VISHAY KOA ROHM
R1101, R1113, R1115, R1117, R224, R225, R226, R227, R311, R327, R404, R405, R501, R509, R510, R601, R608, R609, R729, R922, R923, R924, R930	23	0699-1391	•	CRCW120610K0FKE_ RK73H2BT_1002F MCR18F1002 232272461003L	VISHAY KOA ROHM YAGEO
R1102, R315, R326	3	0699-1394	RESISTOR 14.7K +-1pct .125W TKF TC=0+-100	CRCW120614K7FKE_ RK73H2BT_1472F MCR18F1472 232272461473L	VISHAY KOA ROHM YAGEO
R1104, R1106, R1111, R1112	4	0699-1400	RESISTOR 26.1K +-1pct .125W TKF TC=0+-100	CRCW120626K1FKE_ RK73H2BT_2612F MCR18F2612 232272462613L	VISHAY KOA ROHM YAGEO
R1105, R1107, R1108, R1109, R1114, R1116, R1118, R1120	8	0699-1405	RESISTOR 38.3K +-1pct .125W TKF TC=0+-100	CRCW120638K3FKE_ RK73H2BT_3832F MCR18F3832 232272463833L	VISHAY KOA ROHM YAGEO
R1110, R1119, R314, R406, R407, R933, R934	7	0699-1409		CRCW120656K2FKE_ RK73H2BT_5622F MCR18F5622 232272465623	VISHAY KOA ROHM YAGEO

Reference Designator	Qty	Agilent Part Number	Description	MPN	Manufacturer
R1121, R304, R811	3	0699-1319	RESISTOR 12.1K +-1pct .125W TKF TC=0+-100	CRCW120612K1FKE_ RK73H2BT_1212F MCR18F1212 232272461213L	VISHAY KOA ROHM YAGEO
R201, R202, R204, R209, R320, R929	6	0699-1435	RES-FXD 681 OHM +-1PCT .125W TC 0+-100	CRCW1206681RFKE_ RK73H2BT_6810F MCR18F6810 232272466811	VISHAY KOA ROHM YAGEO
R205, R207, R208, R210, R219, R220, R222, R223, R401, R514, R518, R519, R611, R614, R617	15	0699-1362	, i	CRCW120656R2FKE_ RK73H2BT_56R2F MCR18F56R2 232272465629	VISHAY KOA ROHM YAGEO
R215, R216, R728, R819, R821	5	0699-1381	RESISTOR 3.48K +-1pct .125W TKF TC=0+-100	CRCW12063K48FKE_ RK73H2BT_3481F MCR18F3481 232272463482	VISHAY KOA ROHM YAGEO
R218	1	0699-1347	RESISTOR-FXD 13.3OHM +-1pct .25W TC 0+-1	CRCW120613R3FKE_ RK73H2BT_13R3F MCR18F13R3 232272461339	VISHAY KOA ROHM YAGEO
R302, R312, R402, R403, R507, R925	6	0699-2156	RESISTOR 20K +-1pct .125W TKF TC=0+-100	CRCW120620K0FKE_ RK73H2BT_2002F MCR18F2002 232272462003	VISHAY KOA ROHM YAGEO
R305, R306, R926, R927, R931, R932	6	0699-2489	·	RN732BT_1002B25 BLU-1206 10K .1% 25PPM MCA1206-25 0, 1% P5 10K MCA1206-25 0, 1% P5 10K PCF-W1206R031002BT	KOA RCD COMPONENTS VISHAY BC COMPONENTS VISHAY TT ELECTRONICS
R307	1	0699-2491	RESISTOR 20K +-0.1pct .125W TF TC=0+-25	RN732BT_2002B25 BLU-1206 20K .1% 25PPM MCA1206-25 0, 1% P5 20K MCA1206-25 0, 1% P5 20K W1206R032002BT	KOA RCD COMPONENTS VISHAY BC COMPONENTS VISHAY TT ELECTRONICS


Reference Designator	Qty	Agilent Part Number	Description	MPN	Manufacturer
R309, R904	2	0699-1424	RESISTOR-FXD 237 +-1pct .25W TC 0+-100 12	CRCW1206237RFKE_ RK73H2BT_2370F MCR18F2370	VISHAY KOA ROHM
R316, R318, R713, R716, R718, R801-R808, R822- R824, R916-R919	20	0699-1445	RESISTOR 215K +-1pct .125W TKF TC=0+-100	CRCW1206215KFKE_ RK73H2BT_2153F MCR18F2153 232272462154L	VISHAY KOA ROHM YAGEO
R317, R726	2	0699-1404	RESISTOR 34.8K +-1pct .125W TKF TC=0+-100	CRCW120634K8FKE_ RK73H2BT_3482F MCR18F3482 232272463483	VISHAY KOA ROHM YAGEO
R319	1	0699-2840	·	RN732BT_2501B25 2322741X2502 BLU-1206 2K5 .1% 25PPM MCA1206-25 0, 1% P5 2.5K TNPW12062501BT-9 W1206R032501BT	KOA YAGEO RCD COMPONENTS VISHAY BC COMPONENTS VISHAY TT ELECTRONICS
R321, R731, R902, R903, R928	5	0699-2490	·	RN732BT_1001B25 BLU-1206 1K .1% 25PPM MCA1206-25 0, 1% P5 1K MCA1206-25 0, 1% P5 1K PCF-W1206R031001BT	KOA RCD COMPONENTS VISHAY BC COMPONENTS VISHAY TT ELECTRONICS
R503, R504, R603, R604	4	0699-3215	·	2322741X4029 BLU-1206 40R2 .1% 25PPM PTN1206E40R2BB W1206-R-03-40R2B RN732BT40R2B25	VISHAY BC COMPONENTS RCD COMPONENTS VISHAY TT ELECTRONICS KOA
R506, R512, R605, R612, R722, R725, R901	7	0699-2832	·	RN732BT_2000B25 BLU-1206 200R .1% 25PPM MCA1206-25 0, 1% P5 200R TNPW12062000B W1206R032000BT	KOA RCD COMPONENTS VISHAY BC COMPONENTS VISHAY TT ELECTRONICS

E1445-66502 Parts List


Reference		Agilent			
Designator	Qty	Part Number	Description	MPN	Manufacturer
R508, R513, R515, R516, R606, R613, R615, R616	8	0699-2488	RESISTOR 100 +-0.1pct .125W TF TC=0+-25	RN732BT_1000B25 BLU1206-1000-BT25 MCA1206-25 0, 1% P5 100R MCA1206-25 0, 1% P5 100R PCF-W1206R-03-1000-B	KOA RCD COMPONENTS VISHAY BC COMPONENTS VISHAY TT ELECTRONICS
R511, R610, R820	3	0699-1353	RESISTOR 23.7 +-1pct .125W TKF TC=0+-100	CRCW120623R7FKE_ RK73H2BT_23R7F MCR18F23R7 232272462379	VISHAY KOA ROHM YAGEO
R701, R704, R706, R708	4	0699-2626	RESISTOR 143 +-1pct .125W TKF TC=0+-100	CRCW1206143RFKE_ RK73H2BT_1430F MCR18F1430 232272461431	VISHAY KOA ROHM YAGEO
R702, R703, R705, R707, R709, R710	6	0699-2834	RESISTOR 400 +-0.1pct .125W TF TC=0+-25	RN732BT_4000B25 BLU-1206 400R .1% 25PPM MCA1206-25 0, 1% P5 400R W1206R034000BT TNPW1206400RBEE_	KOA RCD COMPONENTS VISHAY BC COMPONENTS TT ELECTRONICS VISHAY DALE ELECTRONICS
R711, R714	2	0699-1365	RESISTOR 75 +-1pct .125W TKF TC=0+-100	CRCW120675R0FKE_ RK73H2BT_75R0F MCR18F75R0 232272467509	VISHAY KOA ROHM YAGEO
R721, R727	2	0699-1387	RESISTOR 6.81K +-1pct .125W TKF TC=0+-100	CRCW12066K81FKE_ RK73H2BT_6811F 232272466812L MCR18F6811	VISHAY KOA YAGEO ROHM
R723, R730	2	0699-1421	RESISTOR 178 +-1pct .125W TKF TC=0+-100	CRCW1206178RFKE_ RK73H2BT_1780F MCR18F1780 232272461781	VISHAY KOA ROHM YAGEO

Reference		Agilent			
Designator	Qty	Part Number	Description	MPN	Manufacturer
R724	1	0699-2835	RESISTOR 500 +-0.1pct .125W TF TC=0+-25	RN732BT_5000B25 BLU-1206 500R .1% 25PPM MCA1206-25 0, 1% P5 500R PTN1206E5000BB W1206R035000BT	KOA RCD COMPONENTS VISHAY BC COMPONENTS VISHAY TT ELECTRONICS
R809, R812	2	0699-1431	·	CRCW1206464RFKE_ RK73H2BT_4640F MCR18F4640 232272464641	VISHAY KOA ROHM YAGEO
R813, R815	2	0699-1826	RESISTOR 45.3 +-1pct .125W TKF TC=0+-100	CRCW120645R3FKE_ RK73H2BT_45R3F MCR18F45R3 232272464539	VISHAY KOA ROHM YAGEO
R814	1	0699-1430	RESISTOR 422 +-1pct .125W TKF TC=0+-100	CRCW1206422RFKE_ RK73H2BT_4220F MCR18F4220 232272464221	VISHAY KOA ROHM YAGEO
R906, R907, R908, R909, R920, R921	6	0699-0064	RES-FXD 50 OHM +-0.1PCT 0.5W TC 0+-25 020	CMF-6550R0BT-9 H250RBD MBB0207-25 0.1%50R	VISHAY MEGGITT-ELECTRONIC COMPONENTS VISHAY BC COMPONENTS
R910, R911, R913, R914, R915	5	0698-6317	RES-FXD 500 OHM +-0.1PCT 0.125W TC 0+-25	CMF-555000BT-9 MBB0207-25 0.1%500R	VISHAY VISHAY BC COMPONENTS
R912	1	0698-6323	RES-FXD 100 OHM +-0.1PCT 0.125W TC 0+-25	CMF-551000BT-9 MBB0207-25 0.1%100R	VISHAY VISHAY BC COMPONENTS
RP501, RP502, RP601, RP602	4	1810-1159	NET-RES 15 220.0 OHM 16-PIN	4816P-002-221 767161221G SOMC16-01-221G	BOURNS CTS VISHAY
SCR1, SCR2	2	0624-0729	SCREW-TPG 2-56 .25-IN-LG PAN-HD-TORX T8	0624-0729	ILLINOIS TOOL WORKS
T101		9100-4902	TRANSFORMER-RF FREQ. RANGE: 15-400 MH		MINI-CIRCUITS
U1001, U705, U706 U1002		5185-8466	Ltb for 1826-2443 lc,oa,opa621ku (E1445A		
	1	1826-2443	IC OP AMP WB 8 PIN PLSTC-SOIC		
	1	5065-6695	LTB FOR E1445-66502 AND E1445-91002		
	1	1826-2435	IC BFR WB 8 PIN TO-3		


Reference Designator		Agilent Part Number	Description	MPN	Manufacturer
	Qty				
U1101	1	1826-2438	A/D 8-BIT 28-PLCC CMOS	ADC0848CCV-NOPB	NATIONAL SEMICONDUCTOR
U201, U202	2	1820-8832	IC DCDR-DEMUXR CMOS/HC BIN 1-TO-8-LINE		PHILIPS
				74HC137D	NXP
J203, U301, U801	3	1820-6471	IC TRANSCEIVER CMOS/HCT BUS OCTL	SN74HCT652DW	TEXAS INSTRUMENTS
U204, U205	2	1820-7721	IC XLTR ECL/10KH TTL-TO-ECL OCTL	SN10KHT5578DW	TEXAS INSTRUMENTS
U206	1	1820-6524	IC XLTR ECL/10KH TTL-TO-ECL QUAD	MC10H124FNG	ON SEMICONDUCTOR
U207, U210	2	1820-6521	IC GATE ECL/10KH OR-NOR TPL 3-INP	MC10H105FN_G	ON SEMICONDUCTOR
U208	1	1820-5777		MC10H107FNG	ON SEMICONDUCTOR
U209	1	1820-5629	IC FF ECL/10KH D-M/S POS-EDGE-TRIG	MC10H131FNG	ON SEMICONDUCTOR
U302	1	1826-1899	1826-1899	MX7547JP+ AD7547JPZ	MAXIM INTEGRATED PRODUCTS ANALOG DEVICES
U303, U307, U506, U606, U805	5	1826-2420	IC OP AMP LP DUAL 8 PIN PLSTC-SOIC	AD706JRZ	ANALOG DEVICES
U304	1	1826-3162	IC OP AMP PRCN LOW POWER DUAL 8-SOIC	AD822ARZ	ANALOG DEVICES
U305	1	1826-1687		LT1021DCS8-10#PBF	LINEAR TECHNOLOGY
U306, U403, U404, U406	4	1826-1811	IC OP AMP LOW-BIAS-H-IMPD DUAL 8 PIN	TL072ACD	TEXAS INSTRUMENTS
U308	1	1826-1546	IC OP AMP LOW-NOISE SINGLE 8-SOIC	NE5534AD	TEXAS INSTRUMENTS
				NE5534ADG	ON SEMICONDUCTOR
U401	1	1820-5940	IC GATE CMOS/ACT AND QUAD 2-INP	MC74ACT08DG	ON SEMICONDUCTOR
				74ACT08SCX.	FAIRCHILD SEMICONDUCTOR
U402, U405	2	1826-2084	D/A 8-BIT 20-PLCC CMOS	AD7628KP	ANALOG DEVICES
U501, U502, U503	3	1820-7260	IC GATE ECL/10KH OR-NOR QUAD 2-INP	MC10H101FNG	ON SEMICONDUCTOR
U505, U603	2	5065-6611	LTB FOR E1445-66502		
	1	1826-2426	D/A 12-BIT 28-PLCC BPLR		
U601, U602	2	1820-8817	IC BFR ECL/10KH HEX 2-INP	MC10H188FNG	ON SEMICONDUCTOR
U701, U702, U703, U704	4	5185-8467	Ltb for 1826-2444 E1445A		
	1	1826-2444	IC OP AMP WB 8 PIN PLSTC-SOIC		
U707	1	1820-5950	IC INV CMOS/AC HEX 14-SOIC	MC74AC04DG	ON SEMICONDUCTOR
				74AC04SC	FAIRCHILD SEMICONDUCTOR
				SN74AC04D	TEXAS INSTRUMENTS
U802	1	1820-5942	IC TRANSCEIVER CMOS/ACT BUS OCTL	74ACT245SCX.	FAIRCHILD SEMICONDUCTOR
				SN74ACT245DW	TEXAS INSTRUMENTS
				MC74ACT245DWG	ON SEMICONDUCTOR
U901	1	1820-5945	IC GATE CMOS/AC NAND QUAD 2-INP	MC74AC00DG	ON SEMICONDUCTOR
WSH1	1	3050-0891	WASHER-FL MTLC 3.0 3.3-MM-ID 6.85-MM-OD	3050-0891	HOUSE OF METRICS
	0.05	8150-3431	WIRE 30AWG BL 42V KYNAR-PVF	5951-6	ALPHA WIRE
	meter	1		BR212/1-30-021	CORNISH WIRE





E1445-66503 Component Locator





NOTE: LCI1 IS LABELED LCI1* ON -63501
















E1445-66503 page 4 of 9











Agilent E1445A Arbitrary Waveform Generator Component Cross Reference E1445-66503 page 8 of 9

Ref. Des. Layer	X Y	Ref. Des. Layer X Y	Ref. Des. Layer X Y	Ref. Des. Layer X	Y	Ref. Des. Layer X Y	Ref. Des. Layer X	Y	Ref. Des. Layer X Y
C107 1 C108 1 C108 1 C109 1 C109 1 C1010 1 C112 8 C115 8 C115 8 C120 C120 8 C120 C120 8 C120 C120 8 C120 C	675 -3825 775 -3825 275 -7175 275 -3825 275 -7175 275 -5825 275 -7175 2825 -600 2825 -600 2825 -600 2825 -600 2825 -756 2825 -8250	C429 8 3575 -2575 C430 8 1850 -3125 C431 8 2650 -2325 C433 8 3250 -2325 C434 8 1050 -2575 C435 8 1050 -2575 C436 8 1050 -2575 C437 1 650 C438 8 3950 -2575 C502 8 4475 -2050 C502 8 4475 -2050 C502 8 4475 -2050 C503 8 4650 -3275 C504 8 4650 -3275 C505 8 4550 -1350 C506 8 4550 -1350 C507 8 4650 -3275 C511 8 4650 -1355 C512 8 3225 -1550 C513 8 4750 -1255 C514 8 1875 -75 C518 8 4750 -1255 C518 8 4750 -1255 C519 8 4750 -1255 C511 8 4650 -1025 C512 8 3225 -75 C518 8 1875 -75 C519 8 1755 -5125 C511 8 1875 -75 C518 8 2325 -75 C519 8 1755 -5125 C511 8 1875 -75 C518 8 1875 -75 C519 8 1755 -5025 C519 8 1875 -7505 C519 8 1925 -7500 C704 8 1350 -7950 C705 8 1800 -7950 C706 8 1550 -7500 C706 8 1550 -7500 C706 8 1550 -7500 C707 8 1550 -8250 C707 8 1550 -82	C722 1 3350 C723 1 3850 C724 1 3750 C725 1 4400 C726 1 4200 C727 1 4100 C728 1 4200 C728 8 4325 C729 8 4325 C721 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2	-7400		R711	TP568	755 -6150 50 -5900 759 -7275 50 -7285 50 -7590 759 -7225 759 -7225 759 -7225 759 -7225 759 -7225 759 -7225 760 -6605 7605 7605 7605 77850	H420
C422 B C423 B C424 1 C425 I C426 B	1550 -4375 1650 -5075 3850 -4900 3100 -5125 3000 -3925 3850 -5650 3500 -1750 2400 -4725 2525 -775	C708	JM102 8 0 JM401 1 1675 JM402 1 725 JM501 1 3875 JH502 1 3875 JH503 1 3875 JH504 8 4825 JH601 1 3350 JH703 8 1600	-2150 R602 8 3865 -3450 R603 8 235 -4550 R701 8 75 -1575 R703 1 322 -1450 R704 8 95 -1325 R705 1 155 -1750 R706 8 155 -6625 R707 1 165 -7750 R708 1 200 -7600 R709 1 200	-6600 -7700 -8250 -7600 -8250 -8250 -8250 -7800	TP501 1 1225 -5925 TP502 1 1075 -25 TP503 1 1875 -500 TP504 1 1115 -255 TP505 1 2300 -625 TP506 1 4575 -600	U411 ! E U412 ! E U413 ! E U414 ! 16 U415 ! IE U415 ! 45 U417 ! 35 U417 ! 7	350 -4200 150 -4900 150 -4900 150 -4200 150 -5700 150 -5400	LAYER B = CIRCUIT SIDE OF PCBD LAYER 1 = COMPONENT SIDE OF PCBD

Agilent E1445A Arbitrary Waveform Generator

X-Y Cross Reference

E1445-66503 page 9 of 9

Reference		Agilent			
Designator	QTY	Part Number		MPN	Manufacturer
BAG1	1	9222-1440	POUCH-STAT-DISS-CNDCT PE	9222-1440 PACK 66	MAINE POLY SPECIALTY ENTERPRISES
C101, C103, C111, C113, C115, C117, C119, C121, C123, C125	10	0180-3753	CAP-FXD 6.8uF +-20PCT 35V TA	TAJD685M035 ESVD1V685M	AVX NEC ELECTRONICS
C102, C104, C112, C114, C116, C118, C120, C122, C124, C126, C209, C210, C401, C501, C503, C705	16	0160-6497	CAP-FXD 0.1uF +-10pct 50 V CER X7R	12065C104KAT A 2238 581 15649 C1206C104K5RAC C3216X7R1H104KT GRM319R71H104KA01D VJ1206Y104KXAMT	AVX YAGEO KEMET ELECTRONICS TDK MURATA MANUFACTURING VISHAY
C105-C110, C201- C208, C301-C306, C308, C309, C402, C404-C438, C502, C504-C519, C604- C624, C701-C703, C706, C708, C713, C714, C728, C730, C731, C745, C747	108	0160-6736	CAP-FXD 0.01uF +-10pct 50 V CER X7R	12065C103KAT A C1206C103K5RAC C3216X7R1H103K GRM316R71H103KD01D VJ1206Y103KXAMT	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING VISHAY
C130, C716, C734	3	0160-5959	CAP-FXD 33pF +-5pct 50 V CER C0G	08055A330JAT A C0805C330J5GAC C2012COG1H330J GRM2165C1H330JD01D	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING
C601, C602, C715, C740, C741	5	0160-5967	CAP-FXD 100pF +-5pct 50 V CER C0G	08055A101JAT A C0805C101J5GAC C2012COG1H101J GRM2165C1H101JA01D VJ0805A101JXAMT	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING VISHAY

Reference		Agilent			
Designator		Part Number		MPN	Manufacturer
C603, C704, C707,	7	0180-3751	CAP-FXD 1uF +-20PCT 35V TA	TAJB105M035	AVX
C709, C729, C746,				293D105X0035B2E3	VISHAY
C748				ESVB21V105M	NEC ELECTRONICS
				SK-1V105M-RB	ELNA
C719, C722,	4	0160-5957	CAP-FXD 47pF +-5pct 50 V CER C0G	08055A470JAT A	AVX
C742, C744				C0805C470J5GAC C2012COG1H470J	KEMET ELECTRONICS
				GRM2165C1H470JD01D	MURATA MANUFACTURING
				VJ0805A470JXAMT	VISHAY
C725	1	0160-5962	CAP-FXD 15pF +-5pct 50 V CER C0G	08055A150JAT A	AVX
				C0805C150J5GAC	KEMET ELECTRONICS
				C2012COG1H150J	TDK
				GRM2165C1H150JD01D	MURATA MANUFACTURING
C732	1	0160-6096	CAP-FXD 470pF +-5pct 50 V CER C0G	12065A471JAT A	AVX
				C1206C471J5GAC	KEMET ELECTRONICS
				C3216COG1H471J	TDK
				GRM3165C1H471JD01D	MURATA MANUFACTURING
C737	1	0160-5954	CAP-FXD 220pF +-5pct 50 V CER C0G	08055A221JAT A	AVX
				223858016605	YAGEO
				C0805C221J5GAC	KEMET ELECTRONICS
				C2012COG1H221J GRM2165C1H221JA01D	TDK MURATA MANUFACTURING
				GRIVIZ 100C 1HZZ IJAU ID	MORATA MANOFACTORING
DL401	1	1810-1515	DELAY LINE PASSIVE		
			DEVICE W/SINGLE		
E401, E501, E502,	11	9170-1421	CORE-SHIELDING BEAD IMAX 1500MA	MI1210K600R-10	STEWARD
E503, E504, E601,					
E701, E702, E703, E705, E706					
E704	1	1810-1602	DELAY LINE PASSIVE DEVICE	SIP5-201	RHOMBUS INDUSTRIES
-			W/SINGLE		
J103, J104	2	1252-4572	CONN-POST TYPE	5-104550-8	TYCO ELECTRONICS AMP
]	.050-PIN-SPCG-MTG-END		

Reference		Agilent			
Designator		Part Number	Description	MPN	Manufacturer
JM101, JM102,	8	0699-1503		CRCW12060000ZSE_	VISHAY
JM401, JM402,				RK73Z2BT	KOA
JM502, JM504,				MCR18J000	ROHM
JM601, JM703				232271191005	YAGEO
L701, L702, L703,	4	9140-1106	INDUCTOR 1.5uH +-5pct	SMRF1812-151J	GOWANDA ELECTRONICS
L704			3.4W-mmX4.8LG-mm		
L705, L706	2	9140-1428	INDUCTOR 1.2uH +-5pct	SMRF1812-121J	GOWANDA ELECTRONICS
			3.4W-mmX4.8LG-mm		
L707, L708, L709,	4	9140-1111	INDUCTOR 6.8uH +-5pct	SMRF1812-681J	GOWANDA ELECTRONICS
L710			3.4W-mmX4.8LG-mm		
L711, L712	2	9140-1110	INDUCTOR 5.6uH +-5pct 3.4W-mmX4.8LG-mm	SMRF1812-561J	GOWANDA ELECTRONICS
LBL1	1	9320-6241		9320-6241	BRADY
LBL2	+	7121-0850	LABEL-ANTISTATIC 1.81-IN-WD 2.5-IN-LG		R S HUGHES
	1 .	1121 0000		7101	3M
				7121-0850	GM NAMEPLATE
				7121 0000	GIVITY WILL EXTE
LBL3	1	7121-5729	LBL-LNE-PTR; 1.5-IN-WD X .25-IN-LG	THT-45-457-10	BRADY
R101, R421, R601,	5	0699-1318	RESISTOR 1K +-1pct	CRCW12061K00FKE	VISHAY
R602, R704			.125W TKF TC=0+-100	RK73H2BT_1001F	KOA
·				MCR18F1001	ROHM
				232272461002L	YAGEO
R301, R302, R303,	15	0699-1415	RESISTOR 100 +-1pct	CRCW1206100RFKE	VISHAY
R402, R403, R422,				RK73H2BT_1000F	KOA
R423, R424, R425,				MCR18F1000	ROHM
R432, R703, R733,				232272461001L	YAGEO
R734, R735, R736					
R401, R404, R405,	19	0699-2103	RESISTOR 49.9 +-1pct	CRCW120649R9FKE_	VISHAY
R406, R408, R409,			.125W TKF TC=0+-100	RK73H2BT 49R9F	KOA
R410, R413, R414,				MCR18F49R9	ROHM
R416, R418, R419,				232272464999	YAGEO
R420, R426, R427,					
R428, R429, R705,					
R706					


Reference Designator	оту	Agilent Part Number	Description	MPN	Manufacturer
R407, R430, R431, R434, R505	_	0699-1354	RESISTOR 26.1 +-1pct .125W TKF TC=0+-100	CRCW120626R1FKE_ RK73H2BT_26R1F MCR18F26R1 232272462619	VISHAY KOA ROHM YAGEO
R411, R412	2	0699-1427	RESISTOR 316 +-1pct .125W TKF TC=0+-100	CRCW1206316RFKE_ RK73H2BT_3160F MCR18F3160 232272463161	VISHAY KOA ROHM YAGEO
R415, R417, R711, R712, R723, R724	6	0699-1431	RESISTOR 464 +-1pct .125W TKF TC=0+-100	CRCW1206464RFKE_ RK73H2BT_4640F MCR18F4640 232272464641	VISHAY KOA ROHM YAGEO
R501, R502, R707, R709	4	0699-1344	RESISTOR 10 +-1pct .125W TKF TC=0+-100	CRCW120610R0FKE_ RK73H2BT_10R0F MCR18F10R0 232272461009L	VISHAY KOA ROHM YAGEO
R503, R504, R506, R508, R509, R603	6	0699-1391	RESISTOR 10K +-1pct .125W TKF TC=0+-100	CRCW120610K0FKE_ RK73H2BT_1002F MCR18F1002 232272461003L	VISHAY KOA ROHM YAGEO
R701	1	0699-1422	RESISTOR 196 +-1pct .125W TKF TC=0+-100	CRCW1206196RFKE_ RK73H2BT_1960F MCR18F1960 232272461961L	VISHAY KOA ROHM YAGEO
R708	1	0699-1390	RESISTOR 9.09K +-1pct .125W TKF TC=0+-100	CRCW12069K09FKE_ RK73H2BT_9091F MCR18F9091 232272469092	VISHAY KOA ROHM YAGEO

Reference		Agilent			
Designator	_	Part Number		MPN	Manufacturer
R713, R714, R715,	8	0699-1417	RESISTOR 121 +-1pct	CRCW1206121RFKE_	VISHAY
R716, R722, R725,			.125W TKF TC=0+-100	RK73H2BT_1210F	KOA
R726, R727				MCR18F1210	ROHM
				232272461211	YAGEO
R717, R737	2	0699-2712	RESISTOR 255 +-1pct	CRCW1206255RFKE_	VISHAY
			.125W TKF TC=0+-100	RK73H2BT_2550F	KOA
				MCR18F2550	ROHM
				232272462551	YAGEO
R718, R719,	4	0699-1419	RESISTOR 147 +-1pct	CRCW1206147RFKE_	VISHAY
R728, R730			.125W TKF TC=0+-100	RK73H2BT_1470F	KOA
				MCR18F1470	ROHM
				232272461471L	YAGEO
R720, R721,	4	0699-1379	RESISTOR 2.87K +-1pct	CRCW12062K87FKE_	VISHAY
R731, R732			.125W TKF TC=0+-100	RK73H2BT_2871F	KOA
'				MCR18 F2871	ROHM
				232272462872	YAGEO
RP201	1	1810-1128	NET-RES 15 4.7K OHM 16-PIN	767161472G	CTS
				SOMC16-01-472G	VISHAY
				4816P-2-472LF	BOURNS
RP401, RP402,	3	1810-1288	NET-RES 15 100.0 OHM 16-PIN	4816P-002-101	BOURNS
RP403				767161101G	CTS
				SOMC-16-01-101G	VISHAY
U101, U102, U103,	5	1820-5941	IC DCDR-DEMUXR CMOS/ACT	MC74ACT138DG	ON SEMICONDUCTOR
U105, U106			BIN 8-TO-1-LINE	74ACT138SCX	FAIRCHILD SEMICONDUCTOR
U104, U512	2	1820-7312	IC SCHMITT-TRIG CMOS/ACT INV HEX	MC74ACT14DR2G	ON SEMICONDUCTOR
				SN74ACT14D	TEXAS INSTRUMENTS
U201, U202, U203,	7	1820-6471	IC TRANSCEIVER CMOS/HCT	SN74HCT652DW	TEXAS INSTRUMENTS
U204, U208, U209,			BUS OCTL		
U210					

Reference		Agilent			
Designator	QTY	Part Number	Description	MPN	Manufacturer
U205, U206, U207	3	1820-7281	IC TRANSCEIVER CMOS/ACL BUS OCTL	74ACT11245DW	TEXAS INSTRUMENTS
U211	1	1820-8835	IC GATE CMOS/ACT AND TPL 3-INP	MC74ACT11DG	ON SEMICONDUCTOR
U301, U308, U416	3	1820-5937	IC FF CMOS/AC D-TYPE POS-EDGE-TRIG	74AC74SCX-NL MC74AC74DG	FAIRCHILD SEMICONDUCTOR ON SEMICONDUCTOR
U302	1	1820-4998	IC GATE TTL/F OR QUAD 2-INP	74F32SCX. N74F32D SN74F32D N74F32D	FAIRCHILD SEMICONDUCTOR PHILIPS TEXAS INSTRUMENTS NXP
U303, U314, U509	3	1820-5940	IC GATE CMOS/ACT AND QUAD 2-INP	MC74ACT08DG 74ACT08SCX.	ON SEMICONDUCTOR FAIRCHILD SEMICONDUCTOR
U304, U401, U402, U418, U503, U508, U516, U517, U601, U602, U610	11	1820-8830	IC MUXR/DATA-SEL CMOS/ACT 8-TO-1-LINE	74ACT251SCX	FAIRCHILD SEMICONDUCTOR
U305, U417, U510	3	5065-6694	LTB FOR E1445-66503		
U305, U417, U510a	1	1820-8831	IC CNTR TTL/F BIN-DOWN MULTI-MODE		
U306, U419, U511	3	1820-5752	IC FF CMOS/HC D-TYPE POS-EDGE-TRIG COM	MC74HC574ADWG 74HC574D MM74HC574WMX SN74HC574DW 74HC574D	ON SEMICONDUCTOR PHILIPS FAIRCHILD SEMICONDUCTOR TEXAS INSTRUMENTS NXP
U307, U311	2	1820-5938	IC GATE CMOS/ACT NAND QUAD 2-INP	MC74ACT00DG SN74ACT00D 74ACT00SCX	ON SEMICONDUCTOR TEXAS INSTRUMENTS FAIRCHILD SEMICONDUCTOR


Reference		Agilent			
Designator	QTY	Part Number		MPN	Manufacturer
U309, U310, U505,	5	1820-5040	IC FF TTL/F D-TYPE POS-EDGE-TRIG	74F74D	PHILIPS
U506, U507				74F74SCX.	FAIRCHILD SEMICONDUCTOR
				SN74F74D	TEXAS INSTRUMENTS
				74F74D	NXP
U312, U519	2	1820-5944	IC GATE CMOS/ACT OR QUAD 2-INP	MC74ACT32DG	ON SEMICONDUCTOR
				74ACT32SCX.	FAIRCHILD SEMICONDUCTOR
				CD74ACT32M	TEXAS INSTRUMENTS
U403, U404, U420	3	1820-7651	IC XLTR ECL/10KH TTL-TO-ECL OCTL	SN10KHT5543DW	TEXAS INSTRUMENTS
U403, U404, U420 U405	1	1820-6520	IC GATE ECL/10KH TTL-TO-ECL OCTL	MC10H117FN G	ON SEMICONDUCTOR
0405	'		DUAL 3-INP	MC10H117FNG	ON SEMICONDUCTOR
U406, U408, U409,	6	1820-6521	IC GATE ECL/10KH OR-NOR TPL 3-INP	MC10H105FNG	ON SEMICONDUCTOR
U413, U414, U423					
U407	1	1820-6781	IC MUXR/DATA-SEL ECL/10KH 8-TO-1-LINE	MC10H164FNG	ON SEMICONDUCTOR
U410, U412,	4	1820-5629	IC FF ECL/10KH D-M/S POS-EDGE-TRIG	MC10H131FNG	ON SEMICONDUCTOR
U421, U424	-	1020-3029	CTT ECE/TOKITE-W/ST OS-EDGE-TKIG	WC TOTTISTI NO	ON SEMICONDOCTOR
U411	1	5188-2510	LTB FOR 1820-8816		
	1	1820-8816	IC MV ECL/10K MONOSTBL RETRIG		
U415, U425	2	1820-8829	IC XLTR ECL/10KH ECL-TO-TTL OCTL	SN10KHT5541DW	TEXAS INSTRUMENTS
U422	1	1820-5606	IC GATE ECL/10KH AND QUAD 2-INP	MC10H104FN G	ON SEMICONDUCTOR
U501	1	5065-6690	LTB FOR E1445-66503		
	1	1813-0879	CRYSTAL OSC 40.0MHZ 0.005pct		
U502	1	5961-3091	LIFETIME BUY FOR P/N 1813-0831		
	1	1813-0831	CRYSTAL OSC 42.949672MHZ 0.005pct		
U504	1	1820-4687	IC GATE TTL/F NOR QUAD 2-INP	74F02SCX.	FAIRCHILD SEMICONDUCTOR
				N74F02D	PHILIPS
				SN74F02D	TEXAS INSTRUMENTS
				N74F02D	NXP
	2	1820-6141	IC MILYD/DATA OF TTI /F 0 TO 4 LINE	CN74F054DD	TEVAC INICTOL IMPORTO
U514, U515		1020-0141	IC MUXR/DATA-SEL TTL/F 8-TO-1-LINE	SN74F251BD	TEXAS INSTRUMENTS


Reference		Agilent			
Designator	QTY	Part Number	Description	MPN	Manufacturer
U518	1	1820-8728	IC GATE CMOS/ACT NOR QUAD 2-INP	MC74ACT02DR2G 74ACT02SCX.	ON SEMICONDUCTOR FAIRCHILD SEMICONDUCTOR
U603	1	1820-6008	IC MV CMOS/HC MONOSTBL RETRIG DUAL	74HC4538D MM74HC4538M 74HC4538D	PHILIPS FAIRCHILD SEMICONDUCTOR NXP
U605, U606, U608	3	1820-5943	IC MUXR CMOS/ACT QUAD 16-SOIC	74ACT257SC MC74ACT257DG	FAIRCHILD SEMICONDUCTOR ON SEMICONDUCTOR
U607, U617	2	1820-7796	IC DRVR BICMOS/ABT LINE OCTL	74ABT244D SN74ABT244ADW 74ABT244D	PHILIPS TEXAS INSTRUMENTS NXP
U609	1	1820-8947	IC OSC CMOS 32-BIT 68-PLCC		
U611, U612, U613, U614, U615, U616	6	1820-8461	IC FF BICMOS/ABT D-TYPE POS-EDGE-TRIG	74ABT574AD SN74ABT574ADW 74ABT574AD	PHILIPS TEXAS INSTRUMENTS NXP
U618	1	1820-4377	IC GATE TTL/F NAND QUAD 2-INP	74F00SCX. N74F00D SN74F00D N74F00D	FAIRCHILD SEMICONDUCTOR PHILIPS TEXAS INSTRUMENTS NXP
U701	1	5969-5479	LIFETIME BUY FOR 1826-2440		
	1	1826-2440	IC COMPARATOR HS 8 PIN PLSTC-SOIC	AD9696KR	ANALOG DEVICES
U702	1	5000-0021	LTB for 1826-2441		
	1	1826-2441	IC-CONVERTER		
U704	1	1858-0114	TRANSISTOR ARRAY 16-PIN PLSTC SURFACE	MMPQ3906R1 MMPQ3906	ON SEMICONDUCTOR FAIRCHILD SEMICONDUCTOR
U705	1	1826-2203	IC COMPARATOR HS DUAL 20-PLCC	AD96687BPZ	ANALOG DEVICES
	1		PC BOARD BLANK	E1445-26503	SANMINA-SCI





Agilent E1445A Arbitrary Waveform Generator


E1445-66511 Component Locator












Agilent E1445A Arbitrary Waveform Generator

Backplane Periphery

E1445-66511 page 3 of 11

I/O REGISTERS DVB(15:0) O-Pg 3,5,6 ADDRESS DECODERS QUERY RESPONSE QRY_EN* O Pg 3,5 CROSS-GUARD TRANSCEIVERS CROSS_GUARD CONNECTOR /ALE _CNTL(0) DVB(0) OUTGUARD INGUARD +5Vig+15V -15V +20V READ DVB(1) L_CNTL(0) 1 L_CNTL(2) DVB(2) 11 13 CP_EN* VCC 1 _CNTL(3) Pg 3 ○ CP_EN* ⊋ -150 L_CNTL(2) 12 SER_LO_EN* Pg 3 O SER_LO_EN* L_CNTL(4) DVB(4) ∄ †15VL 11 SER HI EN* L CNTL(5) DVB(5) Pg 3 O SER_HI_EN* ≷ R11 475 Ö ‡5Vig Ö ELMER L CNTL(6) DVB(6) RAM_CLK L_CNTL(7) TXD ○ Pg 3 DVB(7) RAM_CLK O Pg 3 INGND ✓ INGDCNTL* ALE O Pg 3 13 /ALE III TEN132 U40D 74HC00 INTERRUPT VECTOR U26 ALE_KILL O Pg 3 70 Y1 13 QR_STB* Pg 2 O TRGIN* CNTL(0) WRITE U_INT_EN* O Pg 6 INT_VEC_STB* L_CNTL(1) 2 ACC 5 L_CNTL(2) 3 L CNTL(0) DVB(8) Pg 3 O IDL STB* L CNTL(1) DVB(9) VCC L CNTL(2) DVB(10) U19 DVB(11) L CNTL(3) RAM_DATA 5 RAM_DATA O Pg 3 L CNTL(4) 15 DVB(12) Pg 2 O TRGOUT* XGDCLK OPg 3 L_CNTL(5) DVB(13) L_CNTL(6) DVB(14) ĘŅD. L_CNTL(7) DVB(15) L_CNTL(7:0) 0 2,3 INGND INGND NTRGLTCHSET RESET INGD_RST O Pg 3 XGD TRG* XGD_TRG* ○ Pg 3 <<u> \</u> NTRGLTCHCLR NTRGLTCHCLR OP9 3 OUTGUART ♦ EXT_TRG_EN* EXT_TRG_EN* O Pg 3 INGND VOLTMETER COMPLETE VCC 1 VCC Vcc U20 ✓ XGDDATA* XGDDATA O Pg 3 VM_CMPL* O Pg 2,3 EXT_TRG_EN* GND ULJ6N137 VCC 1 ACC 5 <u>vcc</u> INGND ₹ R10 475 ₹ R12 ₹ 2.74K CR2 vcc | U4 0C U40.8 TRIGGER 74HC32 74HC00 F XTRG* TRIGGER CR1 74HC112 GND OUTGUARD | INGUARD



CR_SMP_EN

U40B 74HC00

F_XTRG* O-


CR_SMP_EN O

CR SMP* O Pg 6


Agilent E1445A Arbitrary Waveform Generator

Sequencer


E1445-66511 page 4 of 11





E1445-66511 page 5 of 11



E1445-66511 page 6 of 11








Agilent E1445A Arbitrary Waveform Generator

Front Panel Data Connector

E1445-66511 page 7 of 11



SD0(0:9),SD(10:15) O-1-1-4.4.0

HSD0(0:9), HSD(10:15)

Agilent E1445A Arbitrary Waveform Generator

Miscellaneous

E1445-66511 page 8 of 11

-7075 -9025 -9027 -9025 -9027 -7225 -9127 -7225
\$900 \$1900 \$750 \$1400 \$2500 \$2500 \$2500 \$2500 \$2500 \$3350 \$4500 \$4550 \$4500 \$2100 \$200 \$
US14 8 US26 8 US26 8 US26 8 US27 8 US26 8 US27 8 US26 8 US27 8 US
-6600 -7750 -7550 -7550 -7550 -6625 -7575 -6625 -7575 -6625 -7575
11250 11250 11250 11250 11250 11250 11250 11250 11250 11400 10400 10400 10400 11500 11510 10400 11510 10400 11510 10400 11510 10510
208 1 1 1 1 1 1 1 1 1
-2700 -2700
1150 1150 1150 1350 1150 1350 1150 1350 1150 1250 975 1281 1397 1025 475 1800 1025 475 1800 1025 475 1800 1025 475 1800 1025 475 1800 1025 475 1800 7650 7650 7650 7650 7650 7650 7650 76
8
RE24 RE25 RE27 RE27 RE27 RE27 RE27 RE27 RE27 RE27
-5125 - 5
\$5550 6550 7250 6550 7250 6750 7250 7250 7250 7250 7250 7250 7250 7
JM501 JM602 JM602 JM602 JM602 JM602 L308 L308 L308 L308 L308 L308 L308 L308
-3225 -3325 -3325 -3325 -3325 -3225 -3225 -3225 -4225
20.9 -20.9 -20.9 10000 800 7300 1075 12100
C3125 C3126 C3127 C3128 C3128 C3128 C3139 C3131
-5225 -4950 -4950 -5925 -5925 -5925 -5925 -5925 -5925 -5925 -6925 -7125 -6925 -7125
\$050 8875 2890 3750 1050 1150 1150 1150 1150 1150 1175
G3644 1 1 G3648 1 G3648 1
-1775 -1775 -1775 -1775 -1775 -177300 -77775 -8200 -8200 -8002 -80
12550 12500 7300 7400 7500 7500 7500 7500 7500 7500 75
C201

e1445_11 Tue Mar 21 13:00:04 MST 1995

Locations of parts on PCBoard

Ref. Des. Layer X Y


Agilent E1445A Arbitrary Waveform Generator


Component XY Cross Ref

E1445-66511 page 9 of 11

USO1 F P906 USO1 E P906 USO1 D P906 USO1 C P906 USO1 B P906 USO1 A P906	XU3004 XU303 XU303 Pg03 U3525 Pg05 U816 Pg08 U815 B Pg08 U815 A Pg08 U814 D Pg08 U814 B Pg08 U816 U813 Pg08 U816 Pg08 U817 Pg08 U807 Pg08 U808 U808 Pg08 U808 Pg08 U808 U808 U808 Pg08 U808 U808 Pg08 U808 U808 Pg08 U808 U808 Pg08 U808 Pg08 U808
U411 Pg04 U411 Pg04 U409 Pg04 U409 Pg04 U408 Pg04 U407 Pg04	US37
U119 A P901 U118 C P901 U118 B P901 U118 A P901 U118 A P901 U117 P901	Harmonia
R8 1 0 P 9 08 R8 09 P 9 08 R8 08 P 9 08 R8 05 P 9 08 R8 04 P 9 08 R8 04 P 9 08 R8 01 P 9 08 R8 01 P 9 09 R7 03 P 9 07 R7 02 P 9 07 R7 01 P 9 07 R6 38 P 9 06	U116
L302 Pg03 L301 Pg03	R637 Pg06 R638 Pg06 R639 Pg07 Pg07 R639 Pg07 R639 Pg07 R639 Pg07 R639 Pg07 Pg07 R639 Pg07 R639 Pg07 R639 Pg07 R639 Pg07 Pg07 Pg07 R639 Pg07 R639 Pg07 R639 Pg07 R639 R639 R639 Pg07 R639 R639 R639 Pg07 R639 R639 R639 Pg07 R639 R639 R639 Pg07 R639 R6
C3124 Pg03 C3123 Pg03 C3122 Pg03 C3121 Pg03	JM804
C3034 Pg 03 C3033 Pg 03 C3032 Pg 03 C3031 Pg 03	C3120 Pg03 C3118 Pg03 C3119 Pg03 C31117 Pg03 C3115 Pg03 C3115 Pg03 C3115 Pg03 C3115 Pg03 C3114 Pg03 C3114 Pg03 C3114 Pg03 C3116 Pg03 C3110 Pg03 C3110 Pg03 C3110 Pg03 C3110 Pg03 C3106 Pg03 C3107 Pg03 C3108 Pg03 C3107 Pg03 C3108 Pg03 C3108 Pg03 C3098 Pg03 C3098
Agilent E1445A Arbitrary Waveform	C3030
Generator	

Component-to-Page Cross Ref





Agilent E1445A Arbitrary Waveform Generator

Para Ram

E1445-66511 page 11 of 11

Reference		Agilent			
Designator	Quantity	Part Number	Description	MPN	Manufacturer
BAG1	1	9222-1368	BAG-STAT-SHLD POLYM/MET ALY/POLYM FLM	1915 8000 9222-1368 9222-1368 9222-1368 9222-1368 STRATO GREY	3M SIMCO FORCEFIELD STATIC MANAGEMENT SPECIALTY ENTERPRISES STATIC CONTROL COMPONENTS SWIFTMODE BAY PACKAGING
C201	1	0160-6222	CAP-FXD 0.1uF +-10pct 50 V CER X7R	12105C104KAT A C1210C104K5RAC C3225X7R1H104K GRM32MR71H104KA01 L VJ1210Y104KXAMT	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING VISHAY
C202, C3401-C3416, C601, C602	19	0160-6731	CAP-FXD 1000pF +-10pct 50 V CER X7R	12065C102KAT A C1206C102K5RAC C3216X7R1H102K GRM316R71H102KD01 D	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING
C3001-C3135, C3201-C3208, C3301-C3303, C501	147	0160-6736	CAP-FXD 0.01uF +-10pct 50 V CER X7R	12065C103KAT A C1206C103K5RAC C3216X7R1H103K GRM316R71H103KD01 D VJ1206Y103KXAMT	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING VISHAY
C301, C304, C305, C308, C309, C312, C316, C320, C321, C322	10	0160-6497	CAP-FXD 0.1uF +-10pct 50 V CER X7R	12065C104KAT A 2238 581 15649 C1206C104K5RAC C3216X7R1H104KT GRM319R71H104KA01 D VJ1206Y104KXAMT	AVX YAGEO KEMET ELECTRONICS TDK MURATA MANUFACTURING VISHAY
C302, C303, C306, C307, C310, C311, C315, C319	8	0180-3922	CAP-FXD 15uF +-20PCT 20V TA	TAJD156M020 NRD156M20R12	AVX NEC ELECTRONICS

Reference		Agilent			
Designator	Quantity	Part Number	Description	MPN	Manufacturer
C603	1	0160-5967	CAP-FXD 100pF +-5pct 50 V CER C0G	08055A101JAT A C0805C101J5GAC C2012COG1H101J GRM2165C1H101JA01 D VJ0805A101JXAMT	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING VISHAY
C610, C612, C613, C615, C616, C618, C619, C620, C621, C623, C624, C626	12	0180-3751	CAP-FXD 1uF +-20PCT 35V TA	TAJB105M035 293D105X0035B2E3 ESVB21V105M SK-1V105M-RB	AVX VISHAY NEC ELECTRONICS ELNA
C627, C803	2	0160-5961	CAP-FXD 22pF +-5pct 50 V CER COG	08055A220JAT A C0805C220J5GAC C2012COG1H220J GRM2165C1H220JD01 D VJ0805A220JXAMT	AVX KEMET ELECTRONICS TDK MURATA MANUFACTURING VISHAY
CR601, CR603, CR604, CR605	4	1906-0291	DIODE-DUAL 70V 100MA T0-236AA	BAV99 BAV99 BAV99LT1G BAV99X_ BAV99	PHILIPS FAIRCHILD SEMICONDUCTOR ON SEMICONDUCTOR INFINEON TECHNOLOGIES NXP
CR610-CR613, CR615	5	1990-1448	LED-LAMP ARRAY LUM-INT=1.5MCD	553-0302	DIALIGHT
CR614	1	1990-1364	LED-LAMP ARRAY LUM-INT=800UCD	553-0321	DIALIGHT
CR616	1	1990-1507	LED-LAMP LUM-INT=800UCD IF=20MA-MAX	553-0301	DIALIGHT
DL201	1	1810-1609	DELAY LINE PASSIVE DEVICE W/SINGLE		
DL501	1	1810-1515	DELAY LINE PASSIVE DEVICE W/SINGLE		
E306, E307, E601	3	9170-1421	CORE-SHIELDING BEAD IMAX 1500MA	MI1210K600R-10	STEWARD
F301-F305	5	2110-0699	FUSE-SUBMINIATURE 5A 125V NTD AX UL-LST	0251005.	LITTELFUSE

Reference Designator	Quantity	Agilent Part Number	Description	MPN	Manufacturer
HDW1-HDW9	9	0380-1234	SPACER-PRESS-IN 0.500 IN LG; 0.143 IN ID	KFE-143-16-ZI	PENN ENGINEERING & MFG
J101-J104, J106	5	1252-6555	CONN-POST TYPE .100-PIN-SPCG-MTG-END	HTSW-103-07-S-S-LL	SAMTEC
J105	1	1252-1201	CONN-RECT D-SUBMIN 25-CKT 25-CONT	5788800-1 DM11323-D4	TYCO ELECTRONICS AMP HON HAI PRECISION INDUSTRY
J110-J113	4	1250-2012	CONNECTOR-RF BNC FEMALE PC-W-STDFS	5227676-1	TYCO ELECTRONICS AMP
J2, J3	2	1251-5150	CONN-HDR VERT 12-PIN 2.54MM 2-ROW	67996-112HLF	FCI FRAMATOME BERG
JM1, JM2, JM3, JM4, JM5, JM6, JM7	7	1258-0209	JUMPER-REMOVABLE 2 POSITION; .250 IN	68786-202LF 382811-6	FCI FRAMATOME BERG TYCO ELECTRONICS AMP
JM203, JM204, JM402, JM403, JM405, JM501, JM801-JM804	10	0699-1503	RESISTOR 0 CWM	CRCW12060000ZSE_ RK73Z2BT MCR18J000 232271191005	VISHAY KOA ROHM YAGEO
L301, L302, L303	3	9140-1935	INDUCTOR 4.2uH +20pct -20pct	PE-53681	TECHNITROL
L304, L305, L308, L309	4	9140-1113	INDUCTOR 10uH +-5pct 3.4W-mmX4.8LG-mm Q=50	SMRF1812-102J	GOWANDA ELECTRONICS
LBL1	1	7121-0850	LABEL-ANTISTATIC 1.81-IN-WD 2.5-IN-LG	7101 7101 7121-0850	R S HUGHES 3M GM NAMEPLATE
LBL2	1	7121-5729	LBL-LNE-PTR; 1.5-IN-WD X .25-IN-L	THT-45-457-10	BRADY
LBL3	1	9320-6241	LBL-PG-PTR; .625-IN-WD X .25-IN-LG	9320-6241	BRADY
MP1, MP2, MP3, MP4, MP5, MP6, MP7, MP8	8	0624-0729	SCREW-TPG 2-56 .25-IN-LG PAN-HD-TORX T8	0624-0729	ILLINOIS TOOL WORKS
P1, P2	2	1252-1596	CONN-POST TYPE 2.54-PIN-SPCG-MTG-END	10-8557-096-002-025 536010-5 DIN-96CPC-SRI-TR	KYOCERA TYCO ELECTRONICS AMP 3M
P101-P104	4	1252-4481	CONN-POST TYPE .050-PIN-SPCG-MTG-END	5-104549-9	TYCO ELECTRONICS AMP
PCB1	1	E1445-26511	BLANK PCB	E1445-26511	AGILENT TECHNOLOGIES
Q601-Q604	4	5000-0019	LTB for 1853-0728		

Designator	Quantity	Agilent Part Number	Description	MPN	Manufacturer
Q601-Q604a	1	1853-0728	TRANSISTOR PNP SI SOT-223	PZT3906	FAIRCHILD SEMICONDUCTOR
			PD-1000MW		
R101, R115, R301,	12	0699-1384	RESISTOR 4.64K +-1pct	CRCW12064K64FKE_	VISHAY
R401, R402, R403,			.125W TKF TC=0+-100	RK73H2BT_4641F	KOA
R502, R631, R701,				MCR18F4641	ROHM
R703, R803, R805				232272464642L	YAGEO
R102, R103, R104,	5	0699-1378	RESISTOR 2.61K +-1pct	CRCW12062K61FKE_	VISHAY
R105, R801			.125W TKF TC=0+-100	RK73H2BT_2611F	KOA
				MCR18F2611	ROHM
				232272462612L	YAGEO
R106, R113, R114,	15	0699-1415	RESISTOR 100 +-1pct	CRCW1206100RFKE_	VISHAY
R116, R201, R202,			.125W TKF TC=0+-100	RK73H2BT_1000F	KOA
R204, R205, R208,				MCR18F1000	ROHM
R209, R210, R211,				232272461001L	YAGEO
R212, R503, R816					
R107, R108, R109,	6	0699-1391	RESISTOR 10K +-1pct	CRCW120610K0FKE_	VISHAY
R110, R501, R804			.125W TKF TC=0+-100	RK73H2BT_1002F	KOA
				MCR18F1002	ROHM
				232272461003L	YAGEO
R111, R112, R203, R2	9	0699-1437	RESISTOR 825 +-1pct	CRCW1206825RFKE_	VISHAY
			.125W TKF TC=0+-100	RK73H2BT_8250F	KOA
				MCR18F8250	ROHM
				232272468251	YAGEO
R207	1	0699-1375	RESISTOR 1.96K +-1pct	CRCW12061K96FKE_	VISHAY
			.125W TKF TC=0+-100	RK73H2BT_1961F	KOA
				MCR18F1961	ROHM
				232272461962L	YAGEO
R504, R610, R611,	18	0699-1330	RESISTOR 100K +-1pct	CRCW1206100KFKE_	VISHAY
R612, R613, R614,			.125W TKF TC=0+-100	RK73H2BT_1003F	KOA
R615, R616, R617,				MCR18F1003	ROHM
R618, R619, R620,				232272461004L	YAGEO
R621, R622, R623,					
R624, R625, R626					
R602, R627, R628	3	0699-2859	RES-FXD 51 OHM +-5PCT	CRCW251251R0JNE_	VISHAY
			1W TC 0+-200	RK73B3AT510J	KOA
				MCR100J510	ROHM

Reference Designator	Quantity	Agilent Part Number	Description	MPN	Manufacturer
R604, R606, R608	3	0699-2515	RESISTOR 4.7K +-5pct .25W CC		
			TC=-400/+700		
R605, R607, R609	3	0699-6715	RESISTOR 100 OHM +-5pct .5W	CF 1/2 C 101 J	KOA
R629, R632	2	0699-1435	RES-FXD 681 OHM +-1PCT .125W TC 0+-100	CRCW1206681RFKE_ RK73H2BT_6810F MCR18F6810 232272466811	VISHAY KOA ROHM YAGEO
R633, R635	2	0699-1425	RESISTOR 261 +-1pct .125W TKF TC=0+-100	CRCW1206261RFKE_ RK73H2BT_2610F MCR18F2610 232272462611L	VISHAY KOA ROHM YAGEO
R636-R638, R808-R815	11	0699-1348	RESISTOR 14.7 +-1pct .125W TKF TC=0+-100	CRCW120614R7FKE_ RK73H2BT_14R7F MCR18F14R7 232272461479L	VISHAY KOA ROHM YAGEO
RP101, RP102, RP103, RP104, RP201, RP301, RP701	7	1810-1128	NET-RES 15 4.7K OHM 16-PIN	767161472G SOMC16-01-472G 4816P-2-472LF	CTS VISHAY BOURNS
RP202-RP204	3	1810-1288	NET-RES 15 100.0 OHM 16-PIN	4816P-002-101 767161101G SOMC-16-01-101G	BOURNS CTS VISHAY
RP702, RP703	2	1810-1231	NET-RES 8 100.0 OHM 16-PIN	4816P-001-101 767163101G SOMC16-03-101G	BOURNS CTS VISHAY
RP801, RP802	2	1810-1064	NET-RES 15 10.0K OHM 16-PIN	767161103G SOMC-16-01-103G 4816P-2-103LF	CTS VISHAY BOURNS
RVT1, RVT2, RVT3, RVT4	4	0361-1393	RIVET-BLIND DR-PIN UNIV-HD .098DIA	1189-2510	TEXTRON
SP301, SP302	2	3101-2243	SWITCH-DIP RKR 8-1A 0.05A 30VDC	76YY22318ST	GRAYHILL
T601	1	9100-4902	TRANSFORMER-RF FREQ. RANGE: 15-400 MHz	T1-1-KK81	MINI-CIRCUITS

Reference Designator	Quantity	Agilent Part Number	Description	MPN	Manufacturer
U101	1	1820-5845	IC 16-BIT MPU W/COUNTER,	MC68HC000EI10	FREESCALE SEMICONDUCTOR
0101	'	1020 3043	PLCC 10MHZ	WOOOTIOOOOLITO	TREESONEE SEMISONES
U102, U430, U510,	9	1820-5938	IC GATE CMOS/ACT NAND QUAD	MC74ACT00DG	ON SEMICONDUCTOR
U610, U612, U613,			2-INP	SN74ACT00D	TEXAS INSTRUMENTS
U614, U805, U814				74ACT00SCX	FAIRCHILD SEMICONDUCTOR
U103-U110,	15	1820-7281	IC TRANSCEIVER	74ACT11245DW	TEXAS INSTRUMENTS
U114-U117,			CMOS/ACL BUS OCTL		
U128, U301, U302					
U111	1	5188-2562	LTB for 1820-7041		
	1	1820-7041	IC-ASIC		
U112	1	5188-2537	LTB FOR 1820-6693		
	1	1820-6693	IC-ASIC	SCX6B64ABS/U6	NATIONAL SEMICONDUCTOR
U113	1	1818-5236	IC 4K-BIT EEPROM 500-NS CMOS	93LC66B/SN	MICROCHIP TECHNOLOGY
U118, U119	2	1820-4861	IC BFR TTL/F NAND QUAD 2-INP	N74F38D-T	PHILIPS
				N74F38D-T	NXP
U120	1	1820-5075	IC GATE TTL/ALS NAND	SN74ALS20AD	TEXAS INSTRUMENTS
			DUAL 4-INP		
U121, U122, U123,	6	1820-6207	IC TRANSCEIVER TTL/F	74F543D	PHILIPS
U124, U125, U126			REG OCTL	74F543SCX.	FAIRCHILD SEMICONDUCTOR
				SN74F543DW	TEXAS INSTRUMENTS
				74F543D	NXP
U127, U129	2	1820-5218	IC DRVR TTL/F LINE OCTL	74F244D	PHILIPS
0127, 0129		1020-3210	IC DRVR TTE/F LINE OCT	74F244SCX.	FAIRCHILD SEMICONDUCTOR
				SN74F244DW	TEXAS INSTRUMENTS
				74F244DW	NXP
				74F244D	IVAP
U201	1	E1445-88803	PRGMD 1820-8180 OTP	E1445-88803	MEMEC UNITED
	1	1820-8180	IC PLD OTP-EPLD UNPRGMD		
			CMOS 5064		
U204	1	1820-6714	IC DRVR ECL/10KH BUS TPL	MC10H123FNG	ON SEMICONDUCTOR
U205	1	1820-5607	IC RCVR ECL/10KH LINE TPL	MC10H116FNG	ON SEMICONDUCTOR

Reference Designator	Quantity	Agilent Part Number	Description	MPN	Manufacturer
U206	1	1820-7647	IC RGTR ECL/10E STOR 9-BIT	SY10E143JY	MICREL
0200	, i	1020 7017		MC10E143FNG	ON SEMICONDUCTOR
U207	1	1820-7650	IC GATE ECL/10E AND-NAND	SY10E104JY	MICREL
020.		1020 7000	QUINT 2-INP	MC10E104FNG	ON SEMICONDUCTOR
U208-U211	4	1820-7649	IC GATE ECL/10E OR-NOR QUAD 4-INP	MC10E101FNG	ON SEMICONDUCTOR
U212	1	1820-6524	IC XLTR ECL/10KH TTL-TO-ECL QUAD	MC10H124FNG	ON SEMICONDUCTOR
U213	1	1820-5629	IC FF ECL/10KH D-M/S POS-EDGE-TRIG	MC10H131FNG	ON SEMICONDUCTOR
U214, U215, U217, U816	4	1820-8829	IC XLTR ECL/10KH ECL-TO-TTL OCTL	SN10KHT5541DW	TEXAS INSTRUMENTS
U216, U408, U501, U507, U508, U509, U512, U513, U514, U515	10	1820-8461	IC FF BICMOS/ABT D-TYPE POS-EDGE-TRIG	74ABT574AD SN74ABT574ADW 74ABT574AD	PHILIPS TEXAS INSTRUMENTS NXP
U218, U706	2	1820-5053	IC BFR TTL/F LINE QUAD	74F125SCX. N74F125D N74F125D	FAIRCHILD SEMICONDUCTOR PHILIPS NXP
U219, U406, U407, U603, U604, U801	6	1820-6471	IC TRANSCEIVER CMOS/HCT BUS OCTL	SN74HCT652DW	TEXAS INSTRUMENTS
U220	1	1820-7651	IC XLTR ECL/10KH TTL-TO-ECL OCTL	SN10KHT5543DW	TEXAS INSTRUMENTS
U303	1	E1445-88804	PROGRAMMED PART		
	1	1818-4778	IC 1M-BIT OTP 150-NS CMOS		
U304	1	E1445-88805	PROG ROM		
	1	1818-4778	IC 1M-BIT OTP 150-NS CMOS		
U305, U306, U411, U412	4	1818-4218	IC SRAM 256K-BIT 70-NS CMOS 28-SOIC	CY62256NLL-70SNC	CYPRESS SEMICONDUCTOR
U307, U705	2	1820-5940	IC GATE CMOS/ACT AND QUAD 2-INP	MC74ACT08DG 74ACT08SCX.	ON SEMICONDUCTOR FAIRCHILD SEMICONDUCTOR
U308, U310, U311, U312, U313, U314, U315, U316, U317, U802	10	1820-5941	IC DCDR-DEMUXR CMOS/ACT BIN 8-TO-1-LINE	MC74ACT138DG 74ACT138SCX	ON SEMICONDUCTOR FAIRCHILD SEMICONDUCTOR

Reference	0	Agilent	Description	MDM	Manufacturer
Designator	Quantity	Part Number	Description	MPN	Manufacturer
U309, U702, U703, U8	5	1820-7282	IC LCH CMOS/ACL	74ACT11373DW	TEXAS INSTRUMENTS
11404 11704	-	1000 7010	TRANSPARENT OCTL	NOT440T44BB00	ON OF MICONDUCTOR
U401, U701	2	1820-7312	IC SCHMITT-TRIG CMOS/ACT INV HEX	MC74ACT14DR2G SN74ACT14D	ON SEMICONDUCTOR TEXAS INSTRUMENTS
U402, U403, U404,	12	1820-8821	IC TRANSCEIVER CMOS/ACL	74ACT11623DW	TEXAS INSTRUMENTS
U405, U409, U410,			BUS OCTL		
U704, U809, U810,					
U811, U812, U813					
U414, U431, U432,	5	1820-5040	IC FF TTL/F D-TYPE	74F74D	PHILIPS
U433, U511			POS-EDGE-TRIG	74F74SCX.	FAIRCHILD SEMICONDUCTOR
				SN74F74D	TEXAS INSTRUMENTS
				74F74D	NXP
U415	1	1820-5948	IC GATE TTL/F AND TPL 3-INP	74F11SCX.	FAIRCHILD SEMICONDUCTOR
				N74F11D	PHILIPS
				N74F11D	NXP
U416, U417, U418,	12	1820-8822	IC CNTR CMOS/ACT BIN	74ACT161SCX.	FAIRCHILD SEMICONDUCTOR
U419, U420, U421,			SYNCHRO	MC74ACT161D G	ON SEMICONDUCTOR
U422, U423, U426,					
U427, U428, U429					
U424, U425, U434	3	1820-6436	IC SHF-RGTR TTL/F	74F194D	PHILIPS
			SYNC/ASYNC	74F194D	NXP
U435, U436	2	1820-6999	IC GATE TTL/F NAND DUAL	74F20SCX	FAIRCHILD SEMICONDUCTOR
			4-INP 14-SOIC	N74F20D	PHILIPS
				SN74F20D	TEXAS INSTRUMENTS
				N74F20D	NXP
U440-U443,	20	1818-4983	IC 256K-BIT SRAM 15-NS CMOS	IDT71256SA15YG	IDT
U520-U527,				CY7C199CN-15VXC	CYPRESS SEMICONDUCTOR
U530-U537					

Reference Designator	Quantity	Agilent Part Number	Description	MPN	Manufacturer
U502,U503	1	5000-0026	LTB for 1820-6850		
·	2	1820-6850	IC ENCDR TTL/F PRIORITY 8-TO-3-LINE	74F148D	PHILIPS
U504, U506, U602, U617	4	1820-8825	IC GATE CMOS/ACT EXCL-OR QUAD	MC74ACT86DG	ON SEMICONDUCTOR
U505, U611	2	1820-8820	IC GATE CMOS/ACT NAND TPL 3-INP	74ACT10SC MC74ACT10DG	FAIRCHILD SEMICONDUCTOR ON SEMICONDUCTOR
U601	1	1820-5566	IC SCHMITT-TRIG TTL/F INV HEX	74F14SCX. N74F14D N74F14D	FAIRCHILD SEMICONDUCTOR PHILIPS NXP
U605-U609, U615, U806	7	1820-6008	IC MV CMOS/HC MONOSTBL RETRIG DUAL	74HC4538D MM74HC4538M 74HC4538D	PHILIPS FAIRCHILD SEMICONDUCTOR NXP
U616	1	1820-6473	IC FF CMOS/ACT D-TYPE POS-EDGE-TRIG	MC74ACT74DG SN74ACT74D 74ACT74SCX	ON SEMICONDUCTOR TEXAS INSTRUMENTS FAIRCHILD SEMICONDUCTOR
U803	1	1820-6141	IC MUXR/DATA-SEL TTL/F 8-TO-1-LINE	SN74F251BD	TEXAS INSTRUMENTS
U815	1	1820-7796	IC DRVR BICMOS/ABT LINE OCTL	74ABT244D SN74ABT244ADW 74ABT244D	PHILIPS TEXAS INSTRUMENTS NXP
XU303, XU304	2	5969-5438	LTB OF 1200-1417 (MXD/0960)		
,	1	1200-1417	SOCKET-IC-PLCC 32-CONT RECT DIP-SLDR	1-822473-3	TYCO ELECTRONICS AMP

Manual Part Number: 5989-5867EN Printed in U.S.A. November 2006 Copyright © 2006 Agilent Technologies, Inc. All Rights Reserved.

